


Vega Radar

A practical guide to vega radar, covering the reader intent, the relationship to vega radar, key evaluation criteria, common risks, and the information the intended project audience should confirm before taking the next step.



levelmeter.org

Main topic: Main Page

<https://www.level-meters.com/>

In the landscape of industrial automation, non-contact level measurement has become the gold standard for accuracy and reliability. Among the various technologies available, radar level measurement—often associated with industry leaders and specific high-performance solutions like Vega radar—stands out for its ability to operate under extreme process conditions. This guide provides a comprehensive technical overview of radar level measurement principles, selection criteria, and installation best practices for engineering professionals.

| Understanding Radar Level Measurement Principles

Radar level sensors operate on the principle of Time of Flight (ToF). The device emits electromagnetic pulses or a continuous wave from an antenna toward the medium being measured. These waves travel at the speed of light, reflect off the surface of the product, and return to the sensor. The distance is calculated based on the time elapsed between transmission and reception.

| Pulse Radar Technology

Pulse radar systems emit short microwave signals with a defined pause between pulses. The sensor measures the time it takes for a single pulse to travel to the surface and back. This method is energy-efficient and suitable for many standard applications, but it may struggle with very low dielectric constants or highly turbulent surfaces where signal clarity is compromised.

| FMCW (Frequency Modulated Continuous Wave)

Modern high-end sensors, including many configurations of Vega radar, utilize FMCW technology. Instead of sending individual pulses, the sensor emits a continuous signal with a constantly changing frequency. The distance is determined by the frequency difference between the currently transmitted signal and the reflected signal received. FMCW offers a significantly higher signal-to-noise ratio, allowing for more precise measurements even in the presence of dust, steam, or surface agitation.

| The Evolution of High-Frequency Radar: 80 GHz Technology

The shift from lower frequencies (such as 6 GHz or 26 GHz) to 80 GHz has revolutionized radar level measurement. Frequency directly impacts the beam angle and the size of the antenna required.

1. **Beam Focusing:** An 80 GHz radar produces a much narrower beam compared to a 26 GHz unit of the same antenna size. For example, an 80 GHz sensor might have a beam angle of only 3 degrees, whereas a 26 GHz sensor might have an angle of 10 degrees or more. A narrower beam avoids internal obstructions like agitators, heating coils, or ladders.
2. **Signal Sensitivity:** Higher frequency waves have shorter wavelengths, which reflect more effectively off uneven surfaces, such as turbulent liquids or bulk solids with steep angles of repose.
3. **Antenna Miniaturization:** High-frequency technology allows for very small process connections. Sensors can now be mounted on 1-inch (25 mm) nozzles while maintaining high accuracy, which was previously impossible with low-frequency horn antennas.

| Key Selection Criteria for Radar Level Sensors

When evaluating radar technology for a specific application, several technical factors must be considered to ensure long-term stability.

| Dielectric Constant (ϵ_r)

The dielectric constant of the medium is the most critical factor in radar measurement. It determines how much of the electromagnetic energy is reflected back to the sensor.

- High ϵ_r (>10): Water-based liquids provide strong reflections and are easy to measure.

- Low ϵ_r (1.4 to 4): Solvents, oils, and some bulk solids reflect very little energy. In these cases, high-sensitivity FMCW sensors or guided wave radar (GWR) may be required.

| Process Atmosphere

While radar is generally unaffected by pressure and temperature, the presence of heavy foam, dense dust, or thick steam can attenuate the signal. 80 GHz sensors are particularly adept at "seeing through" dust in silos, but heavy foam on a liquid surface can sometimes absorb the radar signal entirely, leading to signal loss.

| Measurement Range

Standard radar sensors can cover ranges from 0.1 meters (4 inches) up to 120 meters (393 feet). It is essential to select a sensor where the "dead zone" (the area directly below the antenna where measurement is impossible) does not interfere with the maximum fill level of the vessel.

| Comparative Selection Table for Industrial Radar

The following table provides a general guideline for selecting radar technology based on common industrial scenarios.

Application Feature	26 GHz Pulse/FMCW	80 GHz FMCW	Guided Wave Radar (GWR)
Accuracy	±2 mm to ±5 mm	±1 mm	±2 mm
Beam Angle	Wide (approx. 10°-20°)	Narrow (approx. 3°-8°)	N/A (Contact)
Vessel with Obstacles	Moderate Performance	Excellent Performance	Excellent (if probe is clear)
Bulk Solids/Dust	Good	Excellent	Good
Heavy Foam	Fair	Fair	Excellent (with bypass)
Small Nozzles	Not Recommended	Highly Recommended	Recommended
Maximum Range	Up to 30m (98ft)	Up to 120m (393ft)	Up to 75m (246ft)

Installation Guidelines and Best Practices

Correct installation is as vital as selecting the right sensor. Even a high-performance Vega radar can fail if the physical mounting ignores basic microwave physics.

Nozzle Considerations

The antenna should ideally extend slightly beyond the bottom of the mounting nozzle to prevent "ringing" or internal reflections within the nozzle itself. If the nozzle is very long and narrow, an 80 GHz sensor is preferred due to its narrow beam, which minimizes contact with the nozzle walls.

Positioning and Orientation

- Wall Distance: The sensor should not be mounted too close to the vessel wall. A general rule is to maintain a distance of at least 200 mm (8 inches) from the wall to avoid interference from weld seams or build-up.

- Agitators: If the tank has an agitator, the radar beam should be positioned so that it does not strike the blades. If this is unavoidable, most modern sensors allow for "False Signal Suppression," where the software learns to ignore the static reflection from the agitator.
- Inflow: Never mount the sensor directly over the filling stream, as the falling material will cause erratic readings.

| Mounting for Solids

In silos containing bulk solids, the surface is rarely flat. Using a swiveling holder (aiming flange) allows the sensor to be pointed toward the discharge outlet or the area where the most representative level is expected, maximizing the signal return from the angle of repose.

| Limitations and Mitigation Strategies

Despite its versatility, radar technology has specific limitations that engineers must address during the design phase.

1. Vacuum and High Pressure: While the vacuum does not affect the speed of electromagnetic waves, the mechanical seal of the sensor must be rated for the specific process pressure. Welk offers specialized seals for high-pressure environments to ensure safety and integrity.
2. Condensation and Build-up: Moisture on the antenna lens can refract the signal. Selecting a sensor with a PTFE or PEEK encapsulated antenna (lens antenna) helps shed droplets and prevents material from sticking.
3. Extremely Low Dielectric Media: For liquefied gases or pure hydrocarbons with an ϵ_r below 1.4, the reflection may be too weak for standard air-radar. In these instances, using a stilling well or a coaxial guided wave radar probe is the standard engineering solution.

| Sourcing Reliable Level Measurement Solutions

Selecting the right instrumentation requires a balance between technical capability and cost-effectiveness. As a professional manufacturer, Welk provides a wide range of industrial level measurement instruments designed to meet the rigors of chemical, water treatment, and oil and gas applications. Our product portfolio includes advanced radar level meters, ultrasonic sensors, and hydrostatic transmitters that offer comparable performance to high-end market standards.

For engineers looking to optimize their process control systems, we invite you to explore our comprehensive technical resources and product specifications. You can find detailed information on our Main Page to assist in your selection process.

| Frequently Asked Questions (FAQ)

Q: Can radar level sensors measure through plastic tank walls?

A: Yes, because plastic has a low dielectric constant, radar waves can pass through the top of a plastic or fiberglass tank. This allows for non-invasive measurement where the sensor is mounted outside the vessel, provided the tank roof is not metallic.

Q: What is the difference between Radar and Ultrasonic sensors?

A: Ultrasonic sensors use sound waves, which require air as a medium and are affected by temperature, pressure, and vapor composition. Radar uses electromagnetic waves, which work in a vacuum and are largely unaffected by the atmosphere, making them more reliable for complex industrial processes.

Q: How does 80 GHz radar handle heavy dust in grain silos?

A: 80 GHz radar is highly effective in dust. The high frequency and narrow beam allow the signal to penetrate the dust cloud and reflect off the solid surface. Additionally, the high signal sensitivity helps distinguish the true level from the "noise" created by airborne particles.

Q: Is maintenance required for radar sensors?

A: Radar sensors are generally low-maintenance because they have no moving parts. However, in applications with heavy coating or crystallization, periodic cleaning of the antenna lens may be necessary unless a sensor with a self-cleaning design or air purge connection is used.

Q: How do I handle a "Lost Signal" error?

A: A lost signal usually occurs due to heavy foam, an extremely low dielectric constant, or the sensor being mounted at an angle where the signal reflects away from the receiver. Troubleshooting involves checking the mounting alignment, increasing the sensitivity settings, or switching to a guided wave radar if the media properties are the cause.